



UNIVERSITI KUALA LUMPUR
Malaysian Institute of Marine Engineering Technology

FINAL EXAMINATION
FEBRUARY 2025 SEMESTER SESSION

SUBJECT CODE	: LED31303
SUBJECT TITLE	: MICROPROCESSOR BASED SYSTEM
PROGRAMME NAME (FOR MPU: PROGRAMME LEVEL)	: DIPLOMA OF ENGINEERING TECHNOLOGY IN ELECTRICAL AND ELECTRONICS (MARINE)
TIME / DURATION	: 09.00 AM - 12.00 PM (3 HOURS)
DATE	: 30 JUNE 2025

INSTRUCTIONS TO CANDIDATES

1. Please read **CAREFULLY** the instructions given in the question paper.
2. This question paper has information printed on both sides of the paper.
3. This question paper consists of **TWO (2)** sections; Section A and Section B.
4. Answer **ALL** question in Section A, and **TWO (2)** questions **ONLY** in Section B.
5. Please write your answers on this answer booklet provided.
6. Answer **ALL** questions in English language **ONLY**.
7. Answer should be written in blue or black ink except for sketching, graphic and illustration.

THERE ARE 5 PAGES OF QUESTIONS, EXCLUDING THIS PAGE.

SECTION A (Total: 60 marks)

INSTRUCTION: Answer ALL questions.
Please use the answer booklet provided.

Question 1

With reference to the Introduction to Microprocessor:

- (a) No matter how complex microprocessors become, they will still follow the same pattern of operations during program execution. Explain the process during microprocessor operation. (10 marks)
- (b) Explain the action of microprocessors responding to special external circumstances. (10 marks)

Question 2

With reference to the Introduction to Microprocessor & Software Architecture.

- (a) Describe **FIVE (5)** key features of the 68000 microprocessors. (10 marks)
- (b) Indicate the registers and flags that get modified after executing each instruction in Table 1. Each instruction is independent from each other.

Register
D0 = \$0012 34AA
D1 = \$0101 1010
D2 = \$0010 1011
D3 = \$0001 1011
D4 = \$1234 5678

Table 1

No.	Instruction	Register	NZVC
i.	ADD.B #\$6B,D1		
ii.	SUB.B #\$5A,D3		
iii.	CLR.B D2		
iv.	MOVE.W \$6244,D4		
v.	ADD.B #\$56, D0		

(10 marks)

Question 3

With reference to Software Architecture:

- (a) Classify **FIVE (5)** primary addressing modes of the 68000 microprocessors with examples. (10 marks)
- (b) Identify the information given by hex file below and determine the value of XX and YY.

S1XX8100227C00008000103C000E4E4F103C00094E4FYY

(10 marks)

SECTION B (Total: 40 marks)

INSTRUCTION: Answer TWO (2) questions ONLY.

Please use the answer booklet provided.

Question 4

With reference to Hardware Architecture and Programming using Assembly Language:

(a) Determine the operation at each state (indicated by arrow) as shown in Figure 1.

(10 marks)




Figure 1

- (b) Outline a program based on the flow chart given in Figure 4. [Hint: $x = D0$, $i = D1$ and $y = D2$]

(10 marks)




Figure 2

Question 5

With reference to Hardware Architecture and Programming using Assembly Language:

- (a) Break down the process of handshake bus control as shown in Figure 3.

(10 marks)




Figure 3

- (b) Outline a program to sum all elements in an array as given in fragment of codes below.

(10 marks)

```
ORG      $3000
ARRAY1   DC.W      5, 6, 7, 11, 32, 52, 4, 3
SUM      DS.W      1
          END
```

Question 6

With reference to Hardware Architecture and Programming using Assembly Language:

- (a) Determine the sequence of events for the write cycle in 68000.
(10 marks)
- (b) Outline a program that will add 30 times the number of 10 and store the result into address \$101B.
(10 marks)

END OF QUESTIONS

